

# VPAR 56 100

LED Par

## DMX mode 1: 2CH

Channels	Value	Function
1	0-255	CW Brightness
2	0-255	WW Brightness

## DMX mode 2: 6CH

Channels	Value	Function
1	0-255	CW Brightness
2	0-255	WW Brightness
3	0-255	Master Dimming
4	0-24	No Function
	25-49	Auto run
	50-74	Pr 2 CW dimming
	75-99	Pr3 WW dimming
	100-124	Pr 4 CW.WW dimming
	125-149	Pr5 CW.WW dimming
	150-174	Pr6 CW.WW hopping
	175-255	Sound active
5	0-255	Sound sensitivity
5	0-255	Built-in Program speed, the large value, the faster speed
6	0-19	LED no strobe
6	20-255	LED strobe, the larger value, the faster speed