

# VBL-02

Blinders &amp; Strobe

## 1, 3, 7 CHANNELS

Col	Col. S	Stage	Value	Description
1		1	000 - 255	Dimmer (0-100%)
	1	2	000 - 255	white 1 (0-100%)
	2	3	000 - 255	white 2 (0-100%)
	3	4		Electronic shutter effect
			0 - 19	Shutter closed
			20 - 24	Shutter open
			25 - 64	Strobe 1 (fast- slow)
			65 - 69	Shutter open
			70 - 84	Strobe 2: Opening pulse (fast - slow)
			85 - 89	Shutter open
			90 - 104	Strobe 3: Closing pulse (fast - slow)
			105 - 109	Shutter open
			110 - 124	Strobe 4: Random strobe (fast - slow)
			125 - 129	Shutter open
			130 - 144	Strobe 5: Random opening pulse (fast - slow)
			145 - 149	Shutter open
			150 - 164	Strobe 6: Random closing pulse (fast - slow)
			165 - 169	Shutter open
			170 - 184	Strobe 7: Burst pulse (fast - slow)
			185 - 189	Shutter open
			190 - 204	Strobe 8: Random burst pulse (fast - slow)
			205 - 209	Shutter open
			210 - 224	Strobe 9: Sine wave (fast - slow)
			225 - 229	Shutter open
			230 - 244	Strobe 10: Sine wave pulse (fast - slow)
			245 - 255	Shutter open

Col	Col. S	Stage	Value	Description
		5	000 ~ 031	No function
			032 ~ 063	AUTO 1
			064 ~ 095	AUTO 2
			096 ~ 127	AUTO 3
			128 ~ 159	AUTO 4
			160 ~ 191	AUTO 5
			192 ~ 223	AUTO 6
			224 ~ 255	AUTO 7
		6	000 ~ 255	AUTO speed
		7	000 ~ 255	ID address selection

