

VLED 804 IP

LED Par

DMX mode 1: 4CH

CH1	CH2	CH3	CH4
R (0~255)	G (0~255)	B (0~255)	W (0~255)

DMX mode 2: 6CH

CH1	CH2	CH3	CH4	CH5	CH6
R (0~255)	G (0~255)	B (0~255)	W (0~255)	Dimmer (0~255)	Strobe (0~255)

DMX mode 3: 8CH

CH1	CH2	CH3	CH4	CH5	CH6		CH7	CH8
Dimmer	R	G	B	W	Program		Speed	Strobe
0~255	0~255	0~255	0~255	0~255	CH2-5	0		0~255
					Pr. 01	1~26	OFF(0-18)	
							R(19-37)	
							RG(38-56)	
							RG(57-75)	
							G(76-94)	
							GB(95-113)	
							B(114-132)	
							RB(133-151)	
							RB(152-170)	
							W(171-189)	
							RW(190-208)	
							GW(209-227)	
							BW(228-246)	
							RGBW(247-255)	

DMX mode 3: 8CH

CH1	CH2	CH3	CH4	CH5	CH6		CH7	CH8
0-255	0-255	0-255	0-255	0-255	Pr.02	27-53	0-255	0-255
					Pr.03	54-80		
					Pr.04	81-107		
					Pr.05	108-134		
					Pr.06	135-161		
					Pr.07	162-188		
					Pr.08	189-215		
					Pr.09	216-242		
					Pr.10	243-255		

